

## Callidus S1000 AM deactivation pad embedded SENSO MINI

### PRODUCT FEATURES

- Plug and play installation
- Large deactivation area
- For installation into the counter
- Status LEDs integrated

### COMPATIBILITY

- AM S1000 deactivator family (13-047)

### MECHANICAL

- Length 35.5 cm (14 in)
- Width 12.3 cm (4.8 in)
- Installation hole 33x10 cm (13x4 in)
- Cable length 1.5 m (59 in)
- Weight 1 kg

### ELECTRICAL

- AM S1000 deactivator required
- Operating frequency 58kHz
- Status indication green and red LED
- Detection distance 21 cm (8.3 in) (DR label)
- Deactivation distance 15 cm (5.9 in)

### ENVIROMENTAL

- Ambient temperature 0–35°C (normal indoor use)
- Relative humidity 0–90% (non-condensing)

**PRODUCT ORDER CODE** 13-081.CES

